

QUICK REFERENCE: real-time clock batteries



Use this guide to select an appropriate replacement battery. Before replacing batteries, read the precautions outlined below. *CAUTION: Improper handling may result in shortened life or in an explosion, and electro-static discharge may damage sensitive logic board circuitry.*

BATTERY

Macintosh model



A302 [742-0003]
Panasonic PX-21
4.5 volt alkaline

Macintosh 128K Macintosh 512K & 512Ke
Macintosh Plus

NOTE: Eveready Energizer 523 batteries are no longer manufactured.



A304 [742-0009]
Tadiran TL-2150
3.6 volt lithium axial pin

Macintosh II & IIfx Macintosh SE

NOTE: Early models use axial pin batteries, later models use the snap-in.

Axial pin batteries are no longer available.



A305 [742-0011]
Tadiran TL-2150
3.6 volt lithium snap-in

AWS [all models]
Classic & Classic II
iMac [all models]
Macintosh IIfx

Centris 610 & 660av

Centris 650

Color Classic

Color Classic II

Macintosh II & IIfx

Macintosh IIfx & IIfx

Macintosh IISI

Macintosh IIfx & IIfx



A306 [742-0011]
SAFT LS14250BA
3.6 volt lithium snap-in

Macintosh LC - LC II

Macintosh LC III

Macintosh LC 475

Macintosh LC 520

Macintosh SE & SE/30

Macintosh TV

Network Server 500

Network Server 700

Performa 200 & 275

Performa 400 - 405 - 476 - 550 - 560 - 600

Performa 6110 & 6118

Power Macintosh 6100

Power Macintosh 7100 - 7200 [except 7220] - 7300 - 7500 - 7600

Power Macintosh 8100 - 8500 - 8600 - 9500 - 9600

Power Macintosh G3 [including G3 Servers and the G3 Blue & White]

Power Macintosh G4 [including G4 Servers]



A307 [742-0011]
Maxell ER3STC
3.6 volt lithium snap-in

Quadra 605

Quadra 610 & 650

Quadra 660av

Quadra 700

Quadra 800 & 840av

Quadra 900 & 950



A318 [922-0750]
RAYOVAC 841
4.5 volt alkaline

Macintosh LC 575 - 578

Macintosh LC 580

Macintosh LC 630

Performa 575 - 578

Performa 580

Performa 630 - 638

Performa 52x0 - 54x0

Performa 62x0 through 64x0

Power Macintosh 4400

Power Macintosh 5200 - 5300 - 5400 - 5500

Power Macintosh 6300

Power Macintosh 6400 - 6500 - 7220

Quadra 630

Twentieth Anniversary Macintosh

OBSERVE THESE PRECAUTIONS with RTC batteries:



Observe ESD precautions to prevent damage to static-sensitive logic board components.

DO NOT use excessive force when inserting or removing RTC batteries, axial leads, battery covers or connectors. Keep replacement batteries in original packaging until ready for use.

DO NOT place a battery on any conductive surface, or expose a battery to excessive heat.

Shortened life or explosion can result from mishandling!